

xlog Module

Elena-Ramona Modroiu
FhG FOKUS

Edited by
Elena-Ramona Modroiu

xlog Module

Edited by and Elena-Ramona Modroiuand Elena-Ramona Modroiu

Copyright © 2003 FhG FOKUS

Revision History

Revision \$Revision: 1.1.2.1 \$ \$Date: 2003/08/05 21:48:08 \$

Table of Contents

1. User's Guide	1
1.1. Overview	1
1.2. Implemented Specifiers	1
1.3. Dependencies	1
1.3.1. SER Modules	1
1.3.2. External Libraries or Applications	1
1.4. Exported Parameters	2
1.4.1. buf_size (integer)	2
1.5. Exported Functions	2
1.5.1. xlog(level, format)	2
1.5.2. xdbg(format)	3
2. Developer's Guide	4
3. Frequently Asked Questions	5

List of Examples

1-1. Set buf_size parameter.....	2
1-2. xlog usage	3
1-3. xdbg usage	3

Chapter 1. User's Guide

1.1. Overview

This module provides the possibility to print user formatted log or debug messages from SER scripts, similar to printf function but now a specifier is replaced with a part of the SIP request. Section 1.2 shows what can be printed out.

1.2. Implemented Specifiers

- %% : '%'
- %Ts : unix time stamp
- %Tf : string formatted time
- %ci : call-id
- %cs : cseq
- %ct : contact header
- %fu : 'From' uri
- %ft : 'From' tag
- %rm : request's method
- %ru : request's r-uri
- %tu : 'To' uri
- %tt : 'To' tag
- %mi : SIP message id
- %pp : process id (pid)
- %is : IP source address

1.3. Dependencies

1.3.1. SER Modules

The following modules must be loaded before this module:

- *No dependencies on other SER modules.*

1.3.2. External Libraries or Applications

The following libraries or applications must be installed before running SER with this module loaded:

- *None.*

1.4. Exported Parameters

1.4.1. buf_size (integer)

Maximum size of the log message.

Default value is 4096.

Example 1-1. Set buf_size parameter

```
...
modparam("xlog", "buf_size", 8192)
...
```

1.5. Exported Functions

1.5.1. xlog(level, format)

Print a formatted message using LOG function.

Meaning of the parameters is as follows:

- *level* - The level that will be used in LOG function. It can be:
 - L_ALERT
 - L_CRIT
 - L_ERR
 - L_WARN
 - L_NOTICE
 - L_INFO
 - L_DBG

What really matters is the third letter of the value.

- *format* - The formatted string to be printed.

Example 1-2. xlog usage

```
...  
xlog("L_ERR", "time [%Tf] method <%rm> r-uri <%ru>\n");  
...
```

1.5.2. xdbg(format)

Print a formatted message using DBG function.

Meaning of the parameters is as follows:

- *format* - The formatted string to be printed.

Example 1-3. xdbg usage

```
...  
xdbg("time [%Tf] method <%rm> r-uri <%ru>\n");  
...
```

Chapter 2. Developer's Guide

The module does not provide any sort of API to use in other SER modules.

Chapter 3. Frequently Asked Questions

1. Where can I find more about SER?

Take a look at <http://iptel.org/ser>.

2. Where can I post a question about this module?

First at all check if your question was already answered on one of our mailing lists:

- <http://mail.iptel.org/mailman/listinfo/serusers>
- <http://mail.iptel.org/mailman/listinfo/serdev>

E-mails regarding any stable version should be sent to [<serusers@iptel.org>](mailto:serusers@iptel.org) and e-mail regarding development versions or CVS snapshots should be send to [<serdev@iptel.org>](mailto:serdev@iptel.org).

If you want to keep the mail private, send it to [<serhelp@iptel.org>](mailto:serhelp@iptel.org).

3. How can I report a bug?

Please follow the guidelines provided at: <http://iptel.org/ser/bugs>